CHECK POS Compatibility Chart

Gold, Silver, Bronze, Traditional, & Check 21+		Check Readers											Imagers						Printers					IMPORTANT NOTES
		All-In-One/Stand-alone Solution	Multi-Merchant Capable	Check 21+ Support (see double-sided imagers in GREEN)	Welch Allyn	CRM431	CR600	Ingenico ez2500	Magtek Mini MICR	Magtek Mini/Magstripe	CR1000i	RDM 5003i/5004i/6003i/6004i/6014i	Magtek MICR image (P/N 22410006 for dial up/dial & P/N 22410004 for IP upload)	Magtek Exe-cells (Double Sided imager)	Magtek STX (Double Sided imager)	RDM eC7009 Series (Double Sided Imager)	P250/P900	Scribe 612	Citizen IDP560/562	IP/Ethernet Support	Wireless Support	Integrated Download File (GETI MUST Build For All Processors)	Independent Download File (GETI Builds Check Only)	DL Swipe Supported (When Magstripe is Present)	GETI Gift Card Support	
ingenico	IVI Checkmanager3000	●															●	●	●				●			Unit must have OS version 2.8 or higher and requires printer for Gold/Silver (cannot use built-in printer from another terminal)…
	AQUA, i5100, i7780		●					●	●			●	●							●			●		●	IP Image Uploads not available at this time…Bronze/Traditional Service req manual Batch "Clear" for proper reporting…No eC5000 Support…
Lipman	Nurit 2080		●		4	4		5	4								●	●	●			●		●	●	Possible memory limitations may exist…
	Nurit 2060, 2085, 3000, 3020, 8320		●		4	4		5	4			●	4			●						●		●	●	Conflicts between applications/protocols could cause support issues…
	Nurit 2090, 3010, 8000, 8400 (Dial-up & IP Only)		●		4	4		5	4			●	4			●				●		●		●	●	Docking Station required to connect check reader/imager to Nurit 8000…
	Valupak 700, 720 w/Built-in Welch Allyn Reader	●	●		4																	●		●	●	
VeriFone	PC Charge (Dial-up Only)								4	4														●		Keyboard Wedge or USB Reader's Only (P/N's 22520001, 22520020, 22530001, 22530005, 22523001, 22523003, 22533001, 22533003)…
	Omni 3200, 3200SE, 3210					4	4	5	4			●				●							●	●		3200 is slow to operate within the bankcard app…Known Memory issue with RBS Lynk Softpay bankcard…
	Omni 3730 LE, Vx510 LE	●				4	4	5	4		●	●	4			●				●			●	●	●	Single Application Terminals and WILL NOT Support Credit, Debit, Gift, etc…With the Check Download…
	Omni 3730, Vx510, Vx570					4	4	5	4		●	●	4			●				●			●	●	●	3730 and Vx510 will not support more than TWO Applications…Works w/Bankcard & Check, OR Check & Gift ONLY…
	Omni 3300, 3740, 3750					4	4	5	4		●	●	4			●				●			●	●	●	Requires At least 6 Meg Of Memory For Multiple Add Value Applications…
HYPERCOM	T7E (T7E requires a ext. printer)					4	4	5	4			●				●	●		●			●				** ALL Hypercom's MUST be on FDR (Omaha), TSYS (VITAL), Global (NDC), Paymentech, Nova, or FDMS (Nashville) **
	T7P, T7Plus, T77		●			4	4	5	4			●				●						●				512 K required for T7 (1 meg for Multi-Merchant)…T77 -G(?) models not supported by GETI's version of SPOS…
	ICE 5500		●			4	4	5	4			●				●						●				
	ICE 5700	●	●																			●				1 meg required for ICE (1.5 meg for Multi-Merchant)…
THALES	T4100, T4200 Series		●			4	4	5	4			●	●			●				●		●			●	Upload handled via Terminal (Use "No Modem" model Imagers to lower cost)...
	Talento		●			4	4	5	4			●				●							●	3		GETI Cannot build the credit load for Talento Terminals…
RDM	RDM Synergy I	●	●																				●	●		
	RDM Synergy II	●	●																				●	●		
4Access	4Access Orion	●	●	●																●		●		●	●	
Commercianti	Mobilescape 5000 (Class B)	●																	●					●		Support is handled by Commerciant…
axalto	Axalto Magic 6100 (Class B)							4				●				●										Support is handled by EMS…
	PrimeTrex IP		●					●				●				●				●			●	●		Auto-Close does not work properly in Multi-App mode…No eC5000 Support…

Bronze & Traditional Only

LinkPoint	LinkPoint 2000, 3000/AIO																●	●	●			●				FDR Only, and no reader capability on the Linkpoints…
VeriFone	Zon Jr, XL300, Tranz 330, & T380					1	1	1	1														●			See notes below…
	Tranz 380x2		●			2	2	2	2														●			Multi-Merchant limited to 2 (with both sides loaded for checks only)…
	Tranz 420 & Tranz 460					1	1	1	1														●			See notes below…
Lipman	8020 (Supports Dial-up only on Checks)		●																							No Reader support on Docking Station for 8020…
COMSTAR	Comstar 3010																		●					●		
	Comstar 8000																		●					●		
	EncomPOS Software (Class B)					●											●	●					●			Setup and Support is handled by EncomPOS…

Revised 1/12/09

Please refer to the new Gateway Solutions Sheet for additional compatibility on Gateway products!

1 = Check reader support available w/ "Standalone" check service only. If using both credit and check on the terminal, MICR information must be manually entered.
2 = Full MICR program available w/Check Only service on 2nd side of terminal, otherwise refer to rule 1.
3 = Supported only in certain applications. Please call Technical Support for details.
4 = Configuration Check(s) are required for this check reader/imager.
5 = This Reader must be mailed into Technical Support to be configured.
6 = Requires USB keyboard emulator & keyboard wedge (USB/Wedge).

***** Be advised that we are unable to incorporate our Value Added Services into certain Class A applications/Processors *****

(Please feel free to call Technical Support at 1-877-438-3249 for details/limitations)